Data sheet | Item number: 207-4301

Разклонителна кутия; за многожилни кабели; Разклонение; Серия 221; конектори макс. 4 mm²; без инсталационни клеми; бял

https://www.wago.com/207-4301

Your benefits:

- Simple, quick and safe connection of up to 60 conductors
- A clearly structured arrangement that's secured on one level
- Highly visible labeling for each individual connection point

Physical data	
Width	225 mm / 8.858 inches
Height from the surface	46 mm / 1.811 inches
Depth	145 mm / 5.709 inches

Material data	
Note (material data)	Information on material data can be found here
Color	бял
Cover color	white
Insulation material	Polycarbonate (PC)
Flammability class per UL94	V0
Fire load	0 MJ
Weight	422.7 g

Environmental requirements	
Ambient temperature (operation)	-25 … +85 °C
Surrounding air temperature (storage)	-25 … +85 °C

Commercial data	
ETIM 8.0	EC001170
ETIM 7.0	EC001170
PU (SPU)	1 Pieces
Country of origin VKOrg Germany	CN
GTIN	4055144019247
Customs tariff number VKOrg Germany	39269097900

Approvals and certificates

Общи одобрения

Approval	Standard	Certificate name
KEMA/KEUR DEKRA Certification B.V.	EN 60670	71-113202

Downloads

Documentation

Additional Information

Technical Section — pdf, 2142.18 KB

Bid Text

ausschreiben.de
207-4301

1 Compatible products

1.1 Optional accessories

1.1.1 Strain relief

1.1.1.1 Specific accessories

Item no.: 207-9301
Комплект аксесоари; Намаляване на натоварването и маркиране; за разклонителна кутия; Артикул 207-4301

Installation notes

Installation

The junction box is designed for surface screw mounting on the wall/ceiling. The cover can be snapped on and off without screws. The connectors are easily mounted by snapping them in, and the marking strips are mounted by simply pushing them in.

Snap the connector into the holder.

Release the connector from the holder.

Conductor termination



Inserting a conductor

Marking

Snap the marking strips into the holder.

Installation

Insert the cable into the strain relief.
The snap-in strain reliefs are designed for cable diameters from 4 mm to 11 mm.

Break the cable entry lid out of the cover.

Snap on the junction box cover.

Open the junction box cover.