Testboy Pocket 100

Digital Multimeter

The Multimeter Testboy Pocket 100 is a further development of the popular Testboy Pocket. Due to its compact construction, many functions and easy operation, it is a valuable aid not only in handcrafts or in the industrial sector, but also for hobby electricians during all standard measurement tasks.

Your advantages
| Breakage and impact-resistant ABS housing
| Highly legible LC display with background illumination
| Data-Hold function
| T-RMS



SPECIFICATIONS

	Testboy Pocket 100	
Indication	LCD with 4 digits	
AC voltage	0–600 V	±0.8 %, ±3 digits
DC voltage	0–600 V	±0.8 %, ±2 digits
Resistance	0–60 Ω	±2.0 %, ±5 digits
Input impedance ACV & DCV	10 MΩ	
AC voltage bandwidth	40–1000 Hz	
Frequency measurement	0–10 MHz	±1.0 %, ±5 digits
Capacity measurement range	0–60 mF	±4.0 %, ±3 digits
Continuity test	Yes, signal sound in case of resistance < 50 Ω	
Diode test	Yes	
Duty cycle in %	Yes	±3.0 %, ±3 digits
Data-Hold function	Yes	
Measurement range selection	Automatic	
Overvoltage category	CAT III 600 V	
Standard	EN 61010-1, EN 61010-2-33	
Operating temperature range	0–40 °C / 32–104 °F (≤ 75 % RH)	
Storage temperature range	-10–50 °C / 14–122 °F (≤ 75 % RH)	
Dimensions	133 x 62 x 27 mm	
Weight	115 g incl. batteries	
Colour	Red/black	
Voltage	2 x 1.5 V AAA, LR03	
Scope of delivery	Incl. measuring lines	